



Enabling DMA on your Windows OS

- Corel Other

Enabling DMA in Windows Vista

1. Log onto Windows as Administrator (or as a user with Administrator privileges).
2. Click the **Start** button, then right-click on **Computer** and choose **Properties** from the pop-up menu. The *System* window appears.
3. Click the **Device Manager** link on the left.
4. In the *Device Manager* window, double-click **IDE ATA/ATAPI controllers** to see the list of controllers.
5. Double-click **Primary IDE Channel** or an **ATA Channel**.
6. In the channel's *Properties* window, click the **Advanced Settings** tab.
7. In the *Device Properties* pane, check **Enable DMA**.
8. Click **OK**. You do not need to restart Windows.

Enabling DMA in Windows XP

1. Log onto Windows as Administrator (or as a user with Administrator privileges).
2. Click the **Start** button, then right-click on **My Computer** and choose **Properties** from the pop-up menu. The **System Properties** window appears.
3. Click the **Hardware** tab, then click **Device Manager**. The **Device Manager** window appears.
4. Double-click **IDE ATA/ATAPI controllers** to see the list of controllers.
5. Double-click **Primary IDE Channel**. The **Primary IDE Channel Properties** window appears.
6. Click the **Advanced Settings** tab.
7. Choose **DMA** if available from the **Transfer Mode list for Device 0**.
8. Click **OK**. You do not need to restart Windows.

Enabling DMA in Windows 2000

1. Log onto Windows as Administrator (or as a user with Administrator privileges).
2. Right-click on the **My Computer** icon on the Windows desktop and choose **Properties** from the pop-up menu. The **System Properties** window appears.
3. Click the **Hardware** tab, then click **Device Manager**. The **Device Manager** window appears.
4. Double-click **IDE ATA/ATAPI controllers** to see the list of controllers.
5. Double-click **Primary IDE Channel**. The **Primary IDE Channel Properties** window appears.
6. Click the **Advanced Settings** tab.
7. Choose **DMA if available** from the **Transfer Mode list for Device 0**. Click **OK**. When Windows asks if you want to restart, **Yes**.

Enabling DMA in Windows 98/98SE/ME

1. Right-click on the **My Computer** icon on the Windows desktop and choose **Properties** from the pop-up menu. The **System Properties** window appears.
 2. Click the **Device Manager** tab.
 3. Double-click **Disk drives** to see the list of disk drives.
 4. Right-click on **IDE DISK** (may have another name, such as **GENERIC IDE DISK**) and choose **Properties** from the pop-up menu. The disk's **Properties** window appears.
 5. Click the **Settings** tab.
 6. Select **DMA** if it is deselected, then click **OK**. When Windows asks if you want to restart, click **Yes**.
-

